

# Matrox RT2000

## Installation procedure for original Millennium as secondary display for RT2000

This document provides information for installing an original Millennium card for use as a second display with Matrox RT2000. For details on installing other types of Millennium cards as a second display with RT2000, such as the Millennium 2 or Millennium G200, see the file named *secondary\_install\_1.pdf*, which is available from the “Compatible secondary display cards” page in the RT2000 Customer Support section of the Matrox Video web site.

**Important** Before installing your secondary display card, make sure that you’ve correctly installed and configured your RT2000 hardware and software as explained in your *RT2000 Installation & User Guide*.

### To install your secondary display card

1. Download the supported display driver for your secondary Millennium card from the “Compatible secondary display cards” page in the RT2000 Customer Support section of the Matrox Video web site.
2. Run the .exe file you downloaded to unzip the driver files to your hard drive.

**Important** You must install the driver for your secondary Millennium card using the procedure described in the following steps. Do **not** run the Matrox PowerDesk setup program (*setup.exe* file) that’s included with the driver files you’ve unzipped to your hard drive.

3. If you have copies of the Windows 98 installation files (.cab files) on your hard drive, temporarily rename the folder that contains these files.
4. Power down your system, then install your Millennium card in a free PCI slot and connect your second computer monitor.
5. Restart your computer. If prompted to insert your Windows 98 CD, click **OK**, but do **not** insert your Windows 98 CD.
6. In the “New Hardware Found” dialog box, click **Cancel**, then click **OK** in response to the warning that no display driver has been installed for your new card.
7. Right-click **My Computer**, choose **Properties**, then click the **Device Manager** tab.
8. Under **Other Devices**, select **PCI Display Adapter**. Then click **Properties > Driver > Update Driver > Next**.
9. Choose to display a list of all drivers in a specific location so that you can select the driver you want, then click **Next**.
10. Select **Display adapters**, then click **Next**.
11. On a Windows Me system, select **Specify a location**, then click **Browse** and specify the drive and folder where you unzipped your Millennium card’s display driver. On a Windows 98 SE system, click **Have Disk**, then click **Browse** and specify the drive and folder where you unzipped your Millennium card’s display driver.
12. Follow the instructions on the screen to complete the software installation.
13. Right-click your Windows desktop background, then click **Properties > Settings**.
14. In the provided display window, click the number “2” monitor, then click **Yes** to enable the monitor.
15. Set your color palette (**Colors**) and display resolution (**Screen area**) to the same settings as your primary monitor. For more information on Windows monitor settings and changing your Windows Display Properties, see your Windows documentation.

### Notes

- Video playback on your second computer monitor will be slow and jerky. When playing back clips in Adobe Premiere, leave the **Monitor** and **Clip** windows on your primary monitor (that is, the monitor connected to your Matrox Millennium G400 Flex 3D Edition card).
- When you extend the Adobe Premiere Timeline onto your second computer monitor, colorful lines appear around the Timeline.

---

© 2000 by Matrox Electronic Systems Ltd. All rights reserved.

**Disclaimer** Matrox Electronic Systems Ltd. reserves the right to make changes in specifications at any time and without notice. The information provided by this document is believed to be accurate and reliable. However, no responsibility is assumed by Matrox Electronic Systems Ltd. for its use; nor for any infringements of patents or other rights of third parties resulting from its use. No license is granted under any patents or patent rights of Matrox Electronic Systems Ltd.